

# Indian Institute of Science

E9-252: Mathematical Methods and Techniques in Signal Processing

Instructor: Shayan G. Srinivasa

Mid Term Exam#1, Fall 2016

---

**Name and SR.No:**

**Instructions:**

- Only four A4 pages/sheets of paper with written notes are allowed.
- The time duration is 3 hrs.
- There are four main questions. None of them have negative marking.
- Attempt all of them with careful reasoning and justification for partial credit.
- Do not panic, do not cheat.
- Good luck!

Question No.	Points scored
1	
2	
3	
4	
Total points	

PROBLEM 1: This problem has 3 parts.

- (1) (a) Is the inverse of a causal LTI system causal? Justify. (b) Is a finite duration signal always stable? Justify (5 pts.)
- (2) Let  $\mathcal{V}$  be a vector space. Suppose  $\mathcal{W}_1$  and  $\mathcal{W}_2$  are subspaces of  $\mathcal{V}$ . Show that  $\mathcal{W}_1 + \mathcal{W}_2$  is a subspace of  $\mathcal{V}$  that contains  $\mathcal{W}_1$  and  $\mathcal{W}_2$ . (10 pts.)
- (3) Consider the space  $\mathcal{V}$  spanned by the vectors  $\mathbf{v}_1 = (1 \ 2 \ 1)^T$ ,  $\mathbf{v}_2 = (1 \ 0 \ 1)^T$  and  $\mathbf{v}_3 = (0 \ -2 \ 0)^T$ . Obtain the basis and dimension of  $\mathcal{V}$  and  $\mathcal{V}^\perp$ . (10 pts.)

PROBLEM 2: This problem has 2 parts.

- (1) Suppose the joint probability mass function (pmf)  $P_{XY}$  is uniform over all the three corners of an equilateral triangle whose base has vertices at  $(-a, 0)$  and  $(a, 0)$ . Obtain the marginal pmfs. Are the random variables (a) independent (b) correlated? (10 pts.)
- (2) Consider the random process  $S(t) = A \cos(\omega t) + B \sin(\omega t)$ , where  $\omega$  is a constant and  $A$  and  $B$  are random variables. (a) What is the necessary condition for this process to be stationary? (b) If  $A$  and  $B$  are uncorrelated with equal variance, then  $S(t)$  is wide sense stationary. Justify if the statement is correct. (15 pts.)

PROBLEM 3: This problem has 2 parts.

- (1) If the low pass filter in a QMF bank is linear phase, the overall transfer function between the reconstructed output and input is guaranteed to be linear phase. Examine if this statement is true/false. Justify. (10 pts.)
- (2) Suppose the low pass filter in a two-channel QMF bank is given by  $H_0(z) = 2 + 6z^{-1} + z^{-2} + 5z^{-3} + z^{-5}$ , obtain a set of stable synthesis filters for perfect recovery. Sketch the polyphase implementation schematic. (15 pts.)

PROBLEM 4: This problem has 2 parts.

- (1) Suppose a discrete time signal  $x[n]$  is first upsampled by 13 followed by downsampling and up-sampling by 3 and downsampling by 13 in the process of sampling rate conversions without any filtering operations in-between. Obtain the frequency domain response at the output after all your simplifications. (5 pts.)
- (2) We need an efficient sampling rate conversion from 32 Ksamples/s to 48 Ksamples/s. From first principles, derive a fully efficient multirate architecture with all associated filters. Sketch the schematic of your multirate system. (20 pts.)